



w.

Connection: Traditional 200 V Channel(s): 4 The GRAS 12AN 4-Channel Power Module is a fourchannel power module with 7-pin LEMO 1 B connectors for externally polarized measurement microphone sets. The inputs are AC-coupled directly to the outputs for a flat frequency response down to 0.05 Hz. It provides the basic features for powering condenser measurement microphones. The polarization voltage can be selected to 200 V for externally polarized microphones or 0 V for prepolarized microphones. The supply voltage for the preamplifiers is ±15 V.

GRAS Sound & Vibration Skovlytoften 33, 2840 Holte, Denmark **www.grasacoustics.com**



Technology

The special features of the 12AN Power Module make it suitable for general use.

The 12AN Power Module is for general use in acoustic measurements both in the laboratory and in the field. If you are looking for a cost-effective solution or a multi-channel power module with direct coupling (no filters) to the output, the 12AN Power Module is a logical choice.

The input signal is coupled to the output without any filtering or A-weighting network.

Because of this, the 12AN Power Module is ideally suited for infra-sound measurements. The lowfrequency cut-off at 0.05 Hz is so low that it will not be the limiting factor in infra-sound measurements. A suitable microphone system for this application is the combination of the <u>GRAS 40AN 1/2" Free-field</u> <u>microphone, low frequencies</u>, and the matching preamplifier, the <u>GRAS 26HG 1/4" Preamplifier, High</u> <u>Impedance</u>.

The polarization voltage is very stable and the sensitivity of the microphone is therefore kept very stable. For this reason, the 12AN Power Module is well suited for microphone calibration.

The 12AN Power Module has four channels for multichannel measurements and calibration setups requiring more than one channel. You can operate the 12AN Power Module on batteries or an external DC power supply. A battery indicator monitors the battery condition.

Compatibility

The 12AN Power Module can be used with all standard, externally polarized microphone sets and standard frontends or data acquisition units.

However, when setting up a measurement chain

with the 12AN Power Module, you need to ensure proper matching of the components so that signal levels and cable lengths do not interfere with the validity of your measurements.

Quality and warranty

The 12AN Power Module is built into a sturdy, anodized aluminum case and built to high-quality standards which enables GRAS to offer 2 years warranty against defective materials and workmanship.

Service

Before leaving the factory, all GRAS products are tested. Should a power module become defective, it can be sent to GRAS for repair.



Specifications

Frequency response (±0.2 dB)HzOutput channel(s)IDirect coupling input to outputILinear modeITypeIInput channel(s), traditional power supplyVPreamplifier supplyVPolarization voltageVOverload indicationIPower amplifier overload detectionIPower supply, batteryVPower supply, batteryVPower consumptionMBattery lifeMFuseMFuseMFuseMFuseMFuseM	•
Direct coupling input to outputImage: Comparison of the second secon	0.05 to 200 k
Linear mode // Comparison of the second seco	4
Type Input channel(s), traditional power supply V Preamplifier supply V Polarization voltage V Overload indication V PC controlable I External filter option I POWER SUPPLY V Power supply, battery V Power consumption MA Battery life MA Battery low indication MA	No
Input channel(s), traditional power supply Input channel(s), traditional power supply Preamplifier supply V Polarization voltage V Overload indication V PC controlable I External filter option I Power amplifier overload detection I POWER SUPPLY V Power supply, battery V Power consumption MA Battery life h	No
Preamplifier supply V Polarization voltage V Overload indication 2 PC controlable 2 External filter option 2 Power amplifier overload detection 2 POWER SUPPLY 2 Power supply, battery 2 Power supply, external 4 Power consumption 2 Battery life 1 Battery low indication 2 2 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3	Traditional power supply (LEMO)
Polarization voltage V Overload indication V PC controlable	4
Overload indicationImage: ControlablePC controlableImage: ControlableExternal filter optionImage: ControlablePower amplifier overload detectionImage: ControlablePOWER SUPPLYImage: ControlablePower supply, batteryImage: ControlablePower supply, externalVdcPower consumptionImage: ControlableBattery lifeh	+-15
PC controlable III and IIII and IIIII and IIII and IIII and IIIII and IIIII and IIIII and IIIIIIIIII	0 / 200
External filter option filter	No
Power amplifier overload detection for a supply battery for a supply, battery for a supply, external for a supply for a su	No
POWER SUPPLY Construction Const	No
Power supply, battery Vdc Power supply, external Vdc Power consumption mA Battery life h	No
Power supply, external Vdc Power consumption mA Battery life h	
Power consumption mA Battery life h Battery low indication	4 x LR6 (AA)
Battery life h	6 to 20
Battery low indication	130
	25
Fuse mA	Yes
	160
Temperature range, operation °C / °F	-10 to +50 / 14 to 122
Weight g / oz	1,200 / 42,329

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.

•

•





Extension cables with 7-pin LEMO connectors

GRAS AA0008	3 m
GRAS AA0009	10 m
GRAS AA0012	30 m
GRAS AA0014	100 m
GRAS AA0020-XX	Custom, XX length in metres

Extension cables with BNC connectors

GRAS AA0034	2 m
<u>GRAS AA0035</u>	3 m
GRAS AA0036	5 m
GRAS AA0037	10 m
GRAS AA0038	30 m
GRAS AA0039-XX	Custom, XX length inmetres

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.

• •



• • •

GRAS Worldwide

Subsidiaries and distributors in more than 40 countries

USA

HEAD OFFICE, DENMARK

GRAS SOUND & VIBRATION Skovlytoften 33 2840 Holte Denmark Tel: +45 4566 4046 www.GRASacoustics.com gras@grasacoustics.com

GRAS SOUND & VIBRATION 9290 SW Nimbus Avenue Beaverton, OR 97008 Tel: 503-627-0832 Toll Free: 800-231-7350 www.GRASacoustics.com sales-usa@grasacoustics.com

.

GRAS SOUND & VIBRATION Unit 115, Gibson House, Ermine Business Park, Huntingdon, Cambridgeshire, PE29 6XU Tel: +44 (0) 7762 584 202 www.GRASacoustics.com sales-uk@grasacoustics.com

CHIN

GRAS SOUND & VIBRATION Room 315, RuiBo Center(T1) Lane683, Shenhong Rd, Minhang District, Shanghai, China, 201107 Tel: +86 21 64203370 www.GRASacoustics.cn cnsales@grasacoustics.com



About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require. GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at www.grasacoustics.com



grasacoustics.com