GRAS 12AQ

2 PC



GRAS 12AQ



Connection: Traditional 200 V / CCP

Channel(s): 2

CCP



Typical applications and use

- General-purpose dual-channel precision measurements
- Intensity measurements
- Standard and custom signal conditioning
- Manual and digital control
- CCP and traditional power supplies
- 0 V or 200 V polarization

Design

It has facilities for both manual control and remote control. Manual control is via its front-panel switches and push-buttons. Remote control is via its RS232 interface.

The 12AQ is for general use in acoustic measurements as well as for intensity measurements; both in the laboratory and in the field.

Traditional Preamplifiers

For traditional preamplifiers such as 26AL (%) or 26AJ and 26AH (%), the 12AQ provides:

- Voltage supply (± 15 V or ± 60 V) for powering up to two microphone preamplifiers
- Polarization voltage (200 V or 0 V) for two condenser microphones

CCP Preamplifiers

For CCP (constant-current power) preamplifiers such as 26CB and 26CC (¼) or 26CA and 26CF (½), the 12AQ provides a constant current supply (4 mA) sourced at 28 V DC for two CCP microphone preamplifiers.

Signal Conditioning

Each channel can be set-up independently in terms of gain, filter, input, output and polarization voltage.

PC

Gain

The gain can be set from – 20 dB to 70 dB in discrete steps of 10 dB.

A series of front-panel LEDs follows and indicates the current gain setting.

Filter

The filter characteristics can be selected from one of the following:

- Lin for linear response with a high-pass filter of 0.2 Hz
- HP for linear response with a high-pass filter of 20 Hz
- AW for an A-weighted response
- Ext for an optional, customized signal-response network (contact GRAS for further details)

Input

The microphone signal can enter the 12AQ via either of the following input sockets on the rear panel.

- BNC sockets for microphones used with CCP preamplifiers
- 7-LEMO sockets for microphones used with traditional preamplifiers

Output

The conditioned output signals, via the BNC output sockets on the rear panel, can be made available as either floating or non-floating.

Polarization voltage

Applicable to 7-pin LEMO preamplifier inputs on the rear panel. Can be set to either 0 V or 200 V.



Preamplifier supply voltage

This can be set to either \pm 15 V or \pm 60 V. The chosen value will apply to both 7-pin LEMO preamplifier inputs.

Power Supply

The 12AQ can be powered either by internal standard alkaline cells (6 x LR14 {C}) or from the included mains/line Adapter for either 115 V AC or 230 V AC.

Warranty

All GRAS products are made of high-quality materials that will ensure life-long stability and robustness. The 12AQ is delivered with a two-year warranty. The warranty does not cover products that are damaged due to negligent use.

Service and Repairs

All repairs are made at GRAS International Support Center located in Denmark. Our Support Center is equipped with the newest test equipment and staffed with dedicated and highly skilled engineers. Upon request, we make cost estimates based on fixed repair categories. If a product covered by warranty is sent for service, it is repaired free of charge, unless the damage is the result of negligent use or other violations of the warranty.



GRAS 12AQ 2

Specifications

Frequency response (±0.1 dB) @ Gain ≤50 dB	Hz	10 to 100 k
Frequency response (±0.2 dB) @ Gain ≤50 dB	Hz	2 to 200 k
Frequency response (±0.1 dB) @ Gain >50 dB	Hz	10 to 20 k
Output channel(s)		2
Output impedance	Ω	100
Direct coupling input to output		No
Inherent noise, LIN (20 Hz to 20 kHz) re input, when not dominated by output	μVrms	<2
Inherent noise, LIN (20 Hz to 200 kHz) re input, when not dominated by output	μVrms	<5
Inherent noise, (20 Hz to 20 kHz) re input, when dominated by output	μVrms	<10
Inherent noise, (20 Hz to 200 kHz) re input, when dominated by output	μVrms	<30
Gain settings, 10 dB steps	dB	-20 to +70
Gain error	dB	± 0.1
Phase matching, equal gain, no filters		IEC 61043
A-weighting filter according to		IEC 61672 Class 1
High-pass filter		3-pole Butterworth, -3 dB @ 20 Hz
Linear mode		Yes
SysCheck level @ 1 kHz	Vrms	1
Туре		Constant Current Power (CCP) and Traditional pow- er supply (LEMO)
Input channel, CCP		2
Input channel(s), traditional power supply		2
Preamplifier supply	V	±15 / ±60
CCP preamplifier supply @ +28 V	mA	4
Polarization voltage	V	0 / 200
Overload indication		Yes



GRAS 12AQ 2

Specifications

Overload level	Vp	9
PC controlable		Yes
External filter option		Yes
Power amplifier overload detection		No
Power supply, battery		6 x LR14 (C)
Power supply, external	Vdc	8 to 18
Battery low indication		Yes
Temperature range, operation	°C / °F	-10 to +50 / 14 to 122
Weight	g / oz	1,350 / 47.62
Weight with batteries	g / oz	1,750 / 61.7

GRAS Sound & Vibration



Ordering info

GRAS EL0002	Battery LR14 (6pcs incl.)
GRAS AA2005	RS-232 cable, 1,8 m
:	()
GRAS AB0002	Power supply 230 VAC to 15 VDC. EU-connector
GRAS AB0006	Power supply 230 VAC to 15 VDC. UK-connector
GRAS AB0003	Power supply 120 VAC to 15 VDC. USA-connector

GRAS RP0001- XX	Customised Signal-response Network for switch pos. Ext. To be factory mounted. Contact your GRAS representative if needed
12 AQ-S20	12AQ Power Module (Excluding Power Supply)

GRAS Sound & Vibration



GRAS Worldwide

Subsidiaries and distributors in more than 40 countries

HEAD OFFICE, DENMARK

GRAS SOUND & VIBRATION

Skovlytoften 33 2840 Holte Denmark Tel: +45 4566 4046 www.GRASacoustics.com gras@grasacoustics.com

USA

GRAS SOUND & VIBRATION

9290 SW Nimbus Avenue Beaverton, OR 97008 Tel: 503-627-0832 Toll Free: 800-231-7350 www.GRASacoustics.com sales-usa@grasacoustics.com

UK

GRAS SOUND & VIBRATION

Unit 115, Gibson House, Ermine Business Park, Huntingdon, Cambridgeshire, PE29 6XU Tel: +44 (0) 7762 584 202 www.GRASacoustics.com sales-uk@grasacoustics.com

CHINA

GRAS SOUND & VIBRATION

Room 315, RuiBo Center(T1) Lane683, Shenhong Rd, Minhang District, Shanghai, China, 201107 Tel: +86 21 64203370 www.GRASacoustics.cn cnsales@grasacoustics.com



About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require.

GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at www.grasacoustics.com

GRAS

An Axiometrix Solutions Brand

grasacoustics.com