

# GRAS 45BC-10

KEMAR

2 CCP



CCP

2

ANSI: S3.36, S3.25

IEC: 60318-4, 60318-7

ITU-T Rec. P.57 Type 3.3

ITU-T Rec. P.58

TEDS 45BC-10 KEMAR

45BC-10

IEC 60318-4

LEMO [GRAS](#)

[45BC-9 KEMAR](#)

2 LEMO

00  
KEMAR Knowles 1972 ( KEMAR  
KEMAR.us ) ANSI  
S3.36/ASA58-2012 IEC 60318-7:2011  
KEMAR KEMAR GRAS supra-aural circumaural  
45BC KEMAR 45BC KEMAR KEMAR  
KEMAR 45BC KEMAR DUT

TEDS 

CCP KEMAR IEEE 1451.4 TEDS v. 1.0  
TEDS

45BC-10	KEMAR	45BC-10 KEMA
USB		
45BC-10	60318-4	GRAS RA0045-S1
KB5000/KB50001		KEMAR
GRAS	ITU-T	P51
1/3	100 dB	20 µPa
kHz	100 Hz	16

60318-4

RA0045-S1

IEC 60318-4 ITU-T P.57

| GRAS 40A0 1/2"

35 Shore

# Specifications

Connector type		BNC
Set sensitivity @ 250 Hz ( $\pm 2$ dB)	mV/Pa	12.5
Set sensitivity @ 250 Hz ( $\pm 2$ dB)	dB re 1V/Pa	-38.5
Theoretical dynamic range lower limit with GRAS preamplifier	dB(A)	25
Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / $\pm 14$ V power supply	dB	151
Theoretical dynamic range upper limit with GRAS CCP preamplifier	dB	146
Resonance frequency	kHz	13.5
Temperature range, operation	°C / °F	-30 to 60 / -22 to 140
Temperature range, storage	°C / °F	-40 to 65 / -40 to 149
Humidity range non condensing	% RH	0 to 95%
ANSI standard		S3.36, S3.25
IEC standard		60318-7
ITU-T recommendations		P. 58
Weight	g / oz	11.45 k / 404
MOUTH SIMULATOR		
Output impedance	Ω	8
Maximum power, continuous	W	10
Maximum power, pulsed 2 sec.	W	50
Input impedance	kΩ	20
Gain	dB	10
Input signal, max.	Vrms	2
Power supply, external	Vdc	24

GRAS Sound & Vibration



<a href="#">GRAS 45BC</a>	KEMAR Head & Torso with GRAS mouth simulator, non-configured
<a href="#">GRAS KB5000</a>	KEMAR Large Right Anthropometric Pinna 35 Shore 00
<a href="#">GRAS KB5001</a>	KEMAR Large Left Anthropometric Pinna 35 Shore 00
GRAS GR0408	External Ear Canal (for calibration, 2 pcs)
GRAS GR0409	Union Nut (for GR0408, 2 pcs)
GRAS GR1874	Ear Simulator Holder (2 pcs)
<a href="#">GRAS RA0045-S1</a>	IEC 60318-4 Ear Simulator, (Prepol.version, 2 pcs)
<a href="#">GRAS 26CS</a>	1/4" CCP Standard Preamplifier with Microdot Connector, Very Short (2 pcs)
<a href="#">GRAS RA0001</a>	Right Angled Adapter for 1/2" Microphone and 1/4" Preamplifier (2 pcs)
<a href="#">GRAS AA0018-S</a>	Microdot-BNC Cable, 35 cm (2 pcs)
<a href="#">GRAS AA0035</a>	3 m BNC - BNC Cable (2 pcs)
<a href="#">GRAS 46BD</a>	1/4" CCP Pressure Standard Microphone Set
<a href="#">GRAS AA0070</a>	Microdot-BNC Cable, 3 m



## Power Modules for Pre-polarized Ear Simulators and Microphones

<a href="#">GRAS 12AL</a>	1-Channel CCP Power Module with A-weighting filter
<a href="#">GRAS 12AQ</a>	2-Channel Universal Power Module with signal conditioning and PC interface

## For Ear Simulator Calibration

<a href="#">GRAS 42AP</a>	Intelligent Pistonphone (250 Hz or 251.2 Hz, 114 dB +/- 0.05 dB)
<a href="#">GRAS 42AA</a>	Pistonphone (250 Hz, 114 dB +/- 0.08 dB)

## Pinna Simulators

<a href="#">GRAS KB5000</a>	Large Right Anthropometric Pinna 35 Shore 00
-----------------------------	--

<a href="#"><u>GRAS KB5001</u></a>	Large Right Anthropometric Pinna 35 Shore 00
<a href="#"><u>GRAS KB0060</u></a>	KEMAR Small Right Ear 55 Shore 00
<a href="#"><u>GRAS KB0061</u></a>	KEMAR Small Left Ear 55 Shore 00
<a href="#"><u>GRAS KB0065</u></a>	KEMAR Large Right Ear 55 Shore 00
<a href="#"><u>GRAS KB0066</u></a>	KEMAR Large Left Ear 55 Shore 00
<a href="#"><u>GRAS KB1060</u></a>	KEMAR Small Right Ear, 35 Shore 00
<a href="#"><u>GRAS KB1061</u></a>	KEMAR Small Left Ear 35 Shore 00
<a href="#"><u>GRAS KB1065</u></a>	KEMAR Large Right Ear 35 Shore 00
<a href="#"><u>GRAS KB1066</u></a>	KEMAR Large Left Ear 35 Shore 00
<a href="#"><u>GRAS KB0090</u></a>	KEMAR Large Right Ear (VA-Style/SQ) 55 Shore 00
<a href="#"><u>GRAS KB0091</u></a>	KEMAR Large Left Ear (VA-Style/SQ) 55 Shore 00
<a href="#"><u>GRAS KB1090</u></a>	KEMAR Large Right Ear (VA-Style) 35 Shore 00
<a href="#"><u>GRAS KB1091</u></a>	KEMAR Large Left Ear (VA-Style) 35 Shore 00

## Ear Mould Simulators

<a href="#"><u>GRAS KB0110</u></a>	Ear Mould Simulator for 2 mm Inner diameter tubing
<a href="#"><u>GRAS KB0111</u></a>	Ear Mould Simulator for 3 mm Inner diameter tubing

## Ear Canal Extension and Microphone Holder Kits (kits with 2 pcs and O-rings)

<a href="#"><u>GRAS RA0237</u></a>	Straight Ear Canal Extension Kit for KEMAR
<a href="#"><u>GRAS RA0238</u></a>	VA-tapered Ear Canal Extension Kit for KEMAR
<a href="#"><u>GRAS RA0239</u></a>	Ear canal Extension Kit w. silicone lining for KEMAR
<a href="#"><u>GRAS RA0240</u></a>	Holder for long 1/2" microphone Kit for KEMAR
<a href="#"><u>GRAS RA0241</u></a>	Holder for short 1/2" microphone Kit for KEMAR
<a href="#"><u>GRAS RA0243</u></a>	Holder for 1/2" microphone Kit for KEMAR
<a href="#"><u>GRAS RA0244</u></a>	O-ring kit for KEMAR, 2 pcs.
<a href="#"><u>GRAS RA0249</u></a>	Straight Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test
<a href="#"><u>GRAS RA0250</u></a>	Tapered Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test

## KEMAR Retrofit Kit for Binaural Hearing Aid Test

### [GRAS RA0251](#)

KEMAR Retrofit Kit for Binaural Hearing Aid Test:  
The Kit includes Ear Holder Plates, mounting bolts and the RA0249 and RA0250 Ear Canal Extension Kits. Included items are made of POM, Nylon and Teflon.

## Extension Cables

GRAS AA0034	BNC-BNC Cable, 2 m
<a href="#">GRAS AA0035</a>	BNC-BNC Cable, 3 m
GRAS AA0036	BNC-BNC Cable, 5 m
<a href="#">GRAS AA0037</a>	BNC-BNC Cable, 10 m

## Flight Case

GRAS KM0094	PELI Case for KEMAR
-------------	---------------------

## Stand for KEMAR

GRAS AL0026	Loudspeaker stand for KEMAR, Ø 35 mm
-------------	--------------------------------------

## Miscellaneous

GRAS KB0000	KEMAR Handbook
GRAS KB0010	T-Shirt for KEMAR

GRAS Sound & Vibration

# GRAS Worldwide

Subsidiaries and distributors in more than 40 countries

## HEAD OFFICE, DENMARK

**GRAS SOUND & VIBRATION**  
Skovlytoften 33  
2840 Holte  
Denmark  
Tel: +45 4566 4046  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[gras@grasacoustics.com](mailto:gras@grasacoustics.com)

## USA

**GRAS SOUND & VIBRATION**  
9290 SW Nimbus Avenue  
Beaverton, OR 97008  
Tel: 503-627-0832  
Toll Free: 800-231-7350  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-usa@grasacoustics.com](mailto:sales-usa@grasacoustics.com)

## UK

**GRAS SOUND & VIBRATION**  
Unit 115, Gibson House,  
Ermine Business Park, Huntingdon,  
Cambridgeshire, PE29 6XU  
Tel: +44 (0) 7762 584 202  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-uk@grasacoustics.com](mailto:sales-uk@grasacoustics.com)

## CHINA

**GRAS SOUND & VIBRATION**  
Room 315, RuiBo Center(T1)  
Lane683, Shenhong Rd,  
Minhang District,  
Shanghai, China, 201107  
Tel: +86 21 64203370  
[www.GRASacoustics.cn](http://www.GRASacoustics.cn)  
[cnsales@grasacoustics.com](mailto:cnsales@grasacoustics.com)



## About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require. GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at [www.grasacoustics.com](http://www.grasacoustics.com)

[grasacoustics.com](http://grasacoustics.com)

**GRAS**  
An Axiometrix Solutions Brand