

# GRAS 45BC-12

KEMAR

LEMO



(200 V/LEMO)

2

ANSI: S3.36

IEC 60318-4 60318-7

ITU-T P.57 3.3 ITU-T P.58

45BC-12 KEMAR

KEMAR

LEMO

[GRAS 45BC-11](#)

□□

KEMAR Knowles 1972 35 Shore 00

[KEMAR.us](#) ANSI

S3.36/ASA58-2012 IEC 60318-7:2011 KEMAR

KEMAR KEMAR GRAS

45BB KEMAR 45BB KEMAR KEMAR

KEMAR 45BB KEMAR - KEMAR

- KEMAR DUT

- KEMAR

□□

45BC-12 KEMAR

USB

“ ”

Read more about the [Anthropometric Pinnae](#).

□□□□

45BC-12

45BC-12 GRAS 44AA GRAS 43BB

KB5000/KB5001 10 kHz

ITU-T Rec. P51 44AA

100 Hz - 16 kHz 1/3 100 dB re. 20µPa THD Rub & Buzz

43BB

43BB IEC 60318-4 40HT

40AH KEMAR 2

KEMAR 5 6

10 kHz IEC 60318-4 10 kHz

13.5 kHz Q Q

26HG GRAS 26AC ¼ 40 G

7 LEMO 26HT

12HF

43BB

Read more about the [43BB Low-noise Ear Simulator System](#).

Set sensitivity @ 250 Hz ( $\pm 2$ dB)	mV/Pa	800
Theoretical dynamic range lower limit with GRAS preamplifier	dB(A)	10.5
Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / $\pm 14$ V power supply	dB	113
Temperature range, operation	$^{\circ}\text{C}$ / $^{\circ}\text{F}$	-30 to 60 / -22 to 140
Temperature range, storage	$^{\circ}\text{C}$ / $^{\circ}\text{F}$	-40 to 65 / -40 to 149
Humidity range non condensing	% RH	0 to 95%
ANSI standard		S3.36
IEC standard		60318-7
ITU-T recommendations		P. 58
Weight	g / oz	11.45 k / 404
MOUTH SIMULATOR		.
Output impedance	$\Omega$	8
Maximum power, continuous	W	10
Maximum power, pulsed 2 sec.	W	50
Input impedance	k $\Omega$	20
Gain	dB	10
Input signal, max.	Vrms	2
Power supply, external	Vdc	24

## GRAS Sound & Vibration



<a href="#">GRAS 45BC</a>	KEMAR Head & Torso with <a href="#">GRAS 44AA Mouth Simulator</a> , Non-configured
<a href="#">GRAS KB5000</a>	Large Right Anthropometric Pinna 35 Shore 00
<a href="#">GRAS KB5001</a>	Large Left Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder (2 pcs)
GRAS GR0408	External Ear Canal (2 pcs)
GRAS GR0409	Union Nut (2 pcs)
<a href="#">GRAS AA0035</a>	BNC-BNC cable, 3 m
<a href="#">GRAS 46BD</a>	1/4" CCP Pressure Standard Microphone Set (for mouth calibration)
<a href="#">GRAS 43BB-1</a>	Low-noise Ear Simulator System, 2 pcs, each comprising:
<a href="#">GRAS RA0001</a>	Right Angled Adapter for 1/2" Microphone and 1/4" Preamplifier
GRAS RA0234	Low-noise Ear Simulator
GRAS 26HG-S1	1/4" Preamplifier with 0.4 m Integrated Cable
GRAS 26HT	Gain and Filter Unit for 40HT
<a href="#">GRAS 12HF</a>	1-Channel Power Module for Low-noise Systems
GRAS AA0059	LEMO cable for low-noise system
<a href="#">GRAS AA0035</a>	BNC-BNC cable, 3 m



<a href="#">GRAS 42AP</a>	Intelligent Pistonphone (250 Hz or 251.2 Hz, 114 dB +/- 0.05 dB)
<a href="#">GRAS 42AA</a>	Pistonphone (250 Hz, 114 dB +/- 0.08 dB)
<a href="#">GRAS RA0090</a>	94 dB Pistonphone Coupler



<a href="#">GRAS KB0060</a>	KEMAR Small Right Ear 55 Shore 00
<a href="#">GRAS KB0061</a>	KEMAR Small Left Ear 55 Shore 00

<a href="#">GRAS KB0065</a>	KEMAR Large Right Ear 55 Shore 00
<a href="#">GRAS KB0066</a>	KEMAR Large Left Ear 55 Shore 00
<a href="#">GRAS KB1060</a>	KEMAR Small Right Ear, 35 Shore 00
<a href="#">GRAS KB1061</a>	KEMAR Small Left Ear 35 Shore 00
<a href="#">GRAS KB1065</a>	KEMAR Large Right Ear 35 Shore 00
<a href="#">GRAS KB1066</a>	KEMAR Large Left Ear 35 Shore 00
<a href="#">GRAS KB0090</a>	KEMAR Large Right Ear (VA-Style/SQ) 55 Shore 00
<a href="#">GRAS KB0091</a>	KEMAR Large Left Ear (VA-Style/SQ) 55 Shore 00
<a href="#">GRAS KB1090</a>	KEMAR Large Right Ear (VA-Style) 35 Shore 00
<a href="#">GRAS KB1091</a>	KEMAR Large Left Ear (VA-Style) 35 Shore 00

□□□□□

<a href="#">GRAS KB0110</a>	Ear Mould Simulator for 2 mm Inner diameter tubing
<a href="#">GRAS KB0111</a>	Ear Mould Simulator for 3 mm Inner diameter tubing

□□□□□□□□□□ (□□□2□□0□□)

<a href="#">GRAS RA0237</a>	Straight Ear Canal Extension Kit for KEMAR
<a href="#">GRAS RA0238</a>	VA-tapered Ear Canal Extension Kit for KEMAR
<a href="#">GRAS RA0239</a>	Ear canal Extension Kit w. silicone lining for KEMAR
<a href="#">GRAS RA0240</a>	Holder for long 1/2" microphone Kit for KEMAR
<a href="#">GRAS RA0241</a>	Holder for short 1/2" microphone Kit for KEMAR
<a href="#">GRAS RA0243</a>	Holder for 1/2" microphone Kit for KEMAR
<a href="#">GRAS RA0244</a>	O-ring kit for KEMAR, 2 pcs.
<a href="#">GRAS RA0249</a>	Straight Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test
<a href="#">GRAS RA0250</a>	Tapered Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test

**KEMAR** □□□□□□□□□□

[GRAS RA0251](#)

KEMAR Retrofit Kit for Binaural Hearing Aid Test:  
The Kit includes Ear Holder Plates, mounting bolts and the RA0249 and RA0250 Ear Canal Extension Kits. Included items are made of POM, Nylon and Teflon.



[GRAS AA0046](#)

3 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system

[GRAS AA0047](#)

10 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system



GRAS KM0094

PELI Case for KEMAR

## KEMAR

GRAS KB3000

Simulation Model of KEMAR with large pinnae

GRAS KB3001

Simulation Model of KEMAR with small pinnae

## KEMAR

GRAS AL0026

Loudspeaker stand for KEMAR, Ø 35 mm



GRAS KB0000

KEMAR Handbook

GRAS KB0010

T-Shirt for KEMAR

GRAS Sound & Vibration

# GRAS Worldwide

Subsidiaries and distributors in more  
than 40 countries

**HEAD OFFICE, DENMARK**  
**GRAS SOUND & VIBRATION**  
Skovlytoften 33  
2840 Holte  
Denmark  
Tel: +45 4566 4046  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[gras@grasacoustics.com](mailto:gras@grasacoustics.com)

**USA**  
**GRAS SOUND & VIBRATION**  
9290 SW Nimbus Avenue  
Beaverton, OR 97008  
Tel: 503-627-0832  
Toll Free: 800-231-7350  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-usa@grasacoustics.com](mailto:sales-usa@grasacoustics.com)

**UK**  
**GRAS SOUND & VIBRATION**  
Unit 115, Gibson House,  
Ermine Business Park, Huntingdon,  
Cambridgeshire, PE29 6XU  
Tel: +44 (0) 7762 584 202  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-uk@grasacoustics.com](mailto:sales-uk@grasacoustics.com)

**CHINA**  
**GRAS SOUND & VIBRATION**  
Room 315, RuiBo Center(T1)  
Lane683, Shenhong Rd,  
Minhang District,  
Shanghai, China, 201107  
Tel: +86 21 64203370  
[www.GRASacoustics.cn](http://www.GRASacoustics.cn)  
[cnsales@grasacoustics.com](mailto:cnsales@grasacoustics.com)



## About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require.

GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at [www.grasacoustics.com](http://www.grasacoustics.com)

[grasacoustics.com](http://grasacoustics.com)

**GRAS**  
An Axiometrix Solutions Brand